

IR COLOR CAMERA

HTC-79G

The CAMERA HTC-79G has a CCD image Sensor and all solid-state circuitry, which provide extremely long life and high sensitivity.

High quality picture, aesthetic and easy to install, the HTC-79G is good complements for your line of CCTV system.

AUTOMATIC GAIN CONTROL (AGC)

The adoption of an AUTOMATIC GAIN CONTROL (AGC) provides clear image in low light condition. During the low light condition, the LED would automatically illuminate

ELECTRONIC IRIS

The color CCD CAMERA HTC-79G incorporates the ELECTRONIC IRIS UP to 1/100,000 sec.

GAMMA CHARACTERISTIC

The color CCD CAMERA HTC-79G incorporates of GAMMA 0.45.

CHANGEABLE LENS MOUNT

The camera HTC-79G includes a 6mm lens and we can also use the optional lens 4.3mm F2.0 lens.

SPECIFICATIONS

ITEMS	HTC-79G
PICK UP ELEMENT	1/3" CCD IMAGE SENSOR
PICTURE ELEMENTS H*V	NTSC:768 * 494, PAL: 7520 * 582
HORIZONTAL RESOLUTION	More than 540 TV lines
HORIZ. SYNC. FREQUENCY	NTSC: 15.734kHz, PAL:15.625kHz
SCANNING SYSTEM	2:1 INTERNAL
SENSITIVITY	0 Lux when IR LED on
SYNCHORIZATION	INTERNAL
S/N RATIO	More than 48 dB
ELECTRONIC SHUTTER	Auto, UP to 1/100,000 sec.
GAMMA	0.45
LENS	6.0mm F1.8
VIDEO OUTPUT	1 Vpp, 75 Ohms
AGC	Auto
POWER SUPPLY	12VDC (+/- 10%)
POWER CONSUMPTION	450mA
DIMENSIONS mm	ψ 68 x w 103.5
WEIGHT gr	500
STORAGE TEMPERATURE	-30 to + 60 Degree C
OPERATING TEMPERATURE	-10 to + 45 Degree C

*SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE.

CONNECTION

1. Use the screws (D) to fix the bracket on the wall.
2. Connect BNC connector (B) to the video output of camera
3. Connect DC JACK (C) to the power of DC 12V.
4. Use the bracket (D) to connect camera.
5. Adjust the view of camera.

LOCATIONS, PARTS NAME & ACCESSORIES

